

## **FUSIONSOLAR RESIDENTIAL SMART PV SOLUTION**

### SUN5000 Series





#### **Efficiency Evolution**

Creating Profitable Return Module-level Optimization Increasing Yield by 5% to 30%



#### Safety Evolution

Protecting Electricity Usage Safety
On the Rooftop
AFCI + RSD



#### **Convenience Evolution**

Embracing PV Lifestyle Module-level Management Disconnection Detection and Location

Technical Specification	SUN2000-450W-P2	SUN2000-600W-P
	Input	
Rated input DC power <sup>1</sup>	450 W	600 W
Absolute max. input voltage	80 V	
MPPT operating voltage range	10-80 V	
Max. short-circuit current (Isc)	14.5 A	
Max. efficiency	99.5%	
Weighted efficiency	99.0%	
Overvoltage category		
5 5 7	Output	
Max. output voltage	80 V	
Max. output current	15 A	
Output bypass <sup>2</sup>	Yes	
Output voltage during standby <sup>3</sup>	0 V	
Output impedanceduring standby	1 kΩ ± 10%	
	Communication	
Communication protocol	MBUS	
'	Standards Compliance	
Safety	IEC62109-1 (class II safety)	
RoHS	Yes	
Fire Safety	VDE-AR-E 2100-712:2018-12	
	General Specifications	
Dimensions (W x H x D)	75 mm x 140 mm x 28 mm (3.0 in. x 5.5 in. x 1.1 in.)	
Weight (including cables)	0.6 kg (1.3 lb.)	
Installation part (optional)	Frame mounting bracket/T-shaped bolt <sup>4</sup>	
Input connector	Staubli MC4	
Input wire length	0.15 m (0.49 ft.)	
Output connector	Staubli MC4	
Output wire length	1.3 m (4.3 ft.)	
Operating temperature/humidity range	-40°C to +85°C 5/0%-100%	
IP rating	IP68	

<sup>\*1</sup> The maximum power of PV module at STC shall NOT exceed the "Rated Input DC Power" of the power optimizer. PV modules with up to +5% power tolerance are allowed.

<sup>\*2</sup> Any power optimizer, which is connected to an operating inverterin a PV string, will be bypassed when it fails.

<sup>\*3</sup> Once the power optimizer stops working, its output voltage is reduced to 0 V.

<sup>\*4</sup> It is for PV module frame/extruded aluminum profile racking system installation.

<sup>\*5</sup> When the operating temperature of the SUN2000-450W-P2/600W-P reaches 70 °C to 85 °C, it may shut down due to over-temperature protection and report an over-temperature alarm. After the temperature decreases, it can automatically resume working without causing any damage.

# Technical Specification

Technical Specification	SUN5000-8K-MAP0	SUN5000-12K-MAP0	
Max. efficiency	Efficiency 98.6%	98.6%	
European weighted efficiency	98.0%	98.2%	
, ,	Input (PV)		
Recommended max. PV power	14,600 Wp	22,000 Wp	
Max. input voltage <sup>1</sup>		00 V	
Operating voltage range <sup>2</sup>		1000 V	
Startup voltage Rated input voltage		50 V	
Max. input current per MPPT	600 V 16 A		
Max. short-circuit current		22 A	
Number of MPP trackers	2		
Max. input per MPP tracker		1	
	Input (DC Battery)		
Compatible battery	LUNA2000-5/10/15-S0 / LUNA2000-7/14/21-S1		
Operating voltage range		600-980 V	
Max. operating current Max. charging power		0 A 100 W	
Max. discharging power	8000 W	12,000 W	
wax. discriding power	Output (On Grid)	12,000 **	
Grid connection		e-phase	
Rated output power	8000 W	12,000 W	
Max. apparent power	8800 VA	13,200 VA	
Rated output voltage		V AC, 240 V AC/415 V AC 3W/N + PE	
Overload capability		0%	
Rated AC grid frequency Max. output current	13.3 A	2/60 Hz	
Adjustable power factor		0.8 lagging	
Max. total harmonic distortion		0.6 tagging 3%	
Max. total Harrionic distortion	Output (Off Grid)	570	
Compatible backup device		3A-T0 (3 phase)	
Rated output power	8000 W	12.000 W	
Rated output voltage		V AC, 240 V AC/415 V AC 3W/N + PE	
110% overload		inuous	
150% overload	5 min (3-phase) / 5 min (Single-phase)	1 min (3-phase) / 5 min (Single-phase)	
200% overload Automatic switchover time		econds nartGuard-63A-T0)	
Automatic switchover time	Protection Feature	IditGudiu-05A-10)	
Asymmetric load		e-phase asymmetric load	
Input-side disconnection device		e-phase asymmetric toau 'es	
Anti-islanding protection		es	
DC reverse polarity protection		es	
Insulation detection	Υ	es es	
DC surge protection	Yes, compatible with TYPE II protection	on class according to EN/IEC 61643-11	
AC surge protection		on class according to EN/IEC 61643-11	
Residual current detection  AC overcurrent protection		<u>′es                                    </u>	
AC overcurrent protection  AC short-circuit protection		'es	
AC overvoltage protection		es	
Arc fault protection		/es	
Terminal temperature detection		Optimizer connectors)	
Ripple receiver control		<u>'es</u>	
Battery charging from grid RSD function		/es /es	
NSD Idriction	General Specification	CS .	
Operating temperature range		(-13°F to +140°F)	
Relative operating humidity		00% RH	
Max. operating altitude		00 m	
Cooling		convection	
Noise Display		9 dB 1 WLAN + FusionSolar APP	
		nart Dongle-WLAN-FE (Optional)	
Communication		G (Optional); EMMA (Optional)	
Weight (incl. mounting brackets)		kg	
Dimensions (incl. mounting	190 mm v 160	) mm x 130 mm	
brackets)			
IP rating		<sup>2</sup> 66	
Nighttime power	Optimizer Compatibility	.5 W	
DC MBUS compatible optimizer <sup>3</sup>	SUN2000-450W-P2, SUN2000-600W-P		
2 C. III DOS COMPUGNIC OPUMIZEI	Standards Compliance (More Available Upon F		
Safety	EN/IEC62109-1	, EN/IEC62109-2	
Grid connection standards	IEC61727, IEC62116, MEA/PEA, G99/G100, Philippine VDE4105, UTE15-712-1/VFR 2019, UNE217002, NTS	C61727, IEC62116, MEA/PEA, G99/G100, Philippine Grid Code Resolution No. 07, NRS 097-2-1, EN50549-1, VDE4105, UTE15-712-1/VFR 2019, UNE217002, NTS631, RD244(UNE217001), PPDS, ROGA, TOR Erzeuger, CEI 0-21:2020-12 V1, C10/C11	
PV System Design <sup>4</sup>	CLINEO	00-8K/12K-MAP0	
r v System Design	SUNSUL	DU-DIN I ZIN-IVIAPU	

PV System Design ⁴	SUN5000-8K/12K-MAP0	
Min. string length (power optimizers)	6	
Max. string length (power optimizers)	35	
Max. DC power per string	12,000 W	

Disclaimer: The preceding values are measured by an internal laboratory of Huawei in a specific environment. The actual values may vary with products, software versions, usage conditions, and environmental factors.

<sup>\*1</sup> The max. input voltage is the upper limit of the DC voltage. Any higher input DC voltage would probably damage the inverter.
\*2 Any DC input voltage beyond the operating voltage range may result in inverter malfunction.
\*3 The SUN5000 Series Inverters must be fully equipped with optimizers, otherwise the system will report errors and can not work.
\*4 SUN2000-450W-P2/600W-P, MERC-600W-PAO can NOT be used in mixture under the same Smart Energy/PV Controller.